

I Restart	Data class	BYTE
	Content	<p>00h: Restart when restart button is actuated</p> <p>01h: Restart after a set time</p> <p>02h: No restart block (default setting)</p> <p>03h: Restart button switches field set, restart after a set time</p> <p>04h: Restart button switches field set, no restart block</p> <p>05h: LMS 2xx operates as a slave, restart after a set time</p> <p>06h: LMS 2xx operates as a slave, immediate restart</p> <p><i>Bit 5:</i></p> <p>0: No motor flap (default setting)</p> <p>1: Use motor flap (output A controls the motor flap, output A cannot be used for evaluating the field)</p> <p><i>Bit 6:</i></p> <p>0: No master (default setting)</p> <p>1: Master (output C outputs the synchronisation cycle)</p> <p><i>Bit 7:</i></p> <p>0: Time basis for restart 1 s (default setting)</p> <p>1: Time basis for restart 1/10 s</p>
	Hex. value	xxh